

Register	Parameter name	Datatype	Multiplier	Read/Write	Range	Base Status	Power Control elements
100	Status Control Area 1	U16	1	Read	0..65535	x	
101	Status Control Area 2	U16	1	Read	0..65535	x	
102	Status Control Area 3	U16	1	Read	0..65535	x	
...							
199	Status Control Area 100	U16	1	Read	0..65535	x	
200	Number of luminaires Control Area 1	U16	1	Read	0..65535	x	
201	Number of luminaires Control Area 2	U16	1	Read	0..65535	x	
202	Number of luminaires Control Area 3	U16	1	Read	0..65535	x	
...							
299	Number of luminaires Control Area 100	U16	1	Read	0..65535	x	
300	Luminaires Unresponsive Control Area 1	U16	1	Read	0..65535	x	
301	Luminaires Unresponsive Control Area 2	U16	1	Read	0..65535	x	
302	Luminaires Unresponsive Control Area 3	U16	1	Read	0..65535	x	
...							
399	Luminaires Unresponsive Control Area 100	U16	1	Read	0..65535	x	
400	Current Power Control Area 1	U16	10	Read	0.0..6553.5kWh		x
401	Current Power Control Area 2	U16	10	Read	0.0..6553.5kWh		x
402	Current Power Control Area 3	U16	10	Read	0.0..6553.5kWh		x
...							
499	Current Power Control Area 100	U16	10	Read	0.0..6553.5kWh		x
500	Max Power Control Area 1	U16	10	Read	0.0..6553.5kWh		x
501	Max Power Control Area 2	U16	10	Read	0.0..6553.5kWh		x
502	Max Power Control Area 3	U16	10	Read	0.0..6553.5kWh		x
...							
599	Max Power Control Area 100	U16	10	Read	0.0..6553.5kWh		x
600	Minimum setpoint Control Area 1 Channel 1	U16	10	Read	0.0..100.0%	x	
601	Minimum setpoint Control Area 2 Channel 1	U16	10	Read	0.0..100.0%	x	
602	Minimum setpoint Control Area 3 Channel 1	U16	10	Read	0.0..100.0%	x	
...							
699	Minimum setpoint Control Area 100 Channel 1	U16	10	Read	0.0..100.0%	x	
700	Minimum setpoint Control Area 1 Channel 2	U16	10	Read	0.0..100.0%	x	
701	Minimum setpoint Control Area 2 Channel 2	U16	10	Read	0.0..100.0%	x	
702	Minimum setpoint Control Area 3 Channel 2	U16	10	Read	0.0..100.0%	x	
...							
799	Minimum setpoint Control Area 100 Channel 2	U16	10	Read	0.0..100.0%	x	
800	Minimum setpoint Control Area 1 Channel 3	U16	10	Read	0.0..100.0%	x	
801	Minimum setpoint Control Area 2 Channel 3	U16	10	Read	0.0..100.0%	x	
802	Minimum setpoint Control Area 3 Channel 3	U16	10	Read	0.0..100.0%	x	
...							
899	Minimum setpoint Control Area 100 Channel 3	U16	10	Read	0.0..100.0%	x	
900	Minimum setpoint Control Area 1 Channel 4	U16	10	Read	0.0..100.0%	x	
901	Minimum setpoint Control Area 2 Channel 4	U16	10	Read	0.0..100.0%	x	
902	Minimum setpoint Control Area 3 Channel 4	U16	10	Read	0.0..100.0%	x	
...							
999	Minimum setpoint Control Area 100 Channel 4	U16	10	Read	0.0..100.0%	x	
1000	Minimum setpoint Control Area 1 Channel 5	U16	10	Read	0.0..100.0%	x	
1001	Minimum setpoint Control Area 2 Channel 5	U16	10	Read	0.0..100.0%	x	
1002	Minimum setpoint Control Area 3 Channel 5	U16	10	Read	0.0..100.0%	x	
...							
1099	Minimum setpoint Control Area 100 Channel 5	U16	10	Read	0.0..100.0%	x	
1100	Minimum setpoint Control Area 1 Channel 6	U16	10	Read	0.0..100.0%	x	
1101	Minimum setpoint Control Area 2 Channel 6	U16	10	Read	0.0..100.0%	x	
1102	Minimum setpoint Control Area 3 Channel 6	U16	10	Read	0.0..100.0%	x	
...							
1199	Minimum setpoint Control Area 100 Channel 6	U16	10	Read	0.0..100.0%	x	
1200	Minimum setpoint Control Area 1 Channel 7	U16	10	Read	0.0..100.0%	x	
1201	Minimum setpoint Control Area 2 Channel 7	U16	10	Read	0.0..100.0%	x	
1202	Minimum setpoint Control Area 3 Channel 7	U16	10	Read	0.0..100.0%	x	
...							
1299	Minimum setpoint Control Area 100 Channel 7	U16	10	Read	0.0..100.0%	x	
1300	Minimum setpoint Control Area 1 Channel 8	U16	10	Read	0.0..100.0%	x	
1301	Minimum setpoint Control Area 2 Channel 8	U16	10	Read	0.0..100.0%	x	
1302	Minimum setpoint Control Area 3 Channel 8	U16	10	Read	0.0..100.0%	x	
...							
1399	Minimum setpoint Control Area 100 Channel 8	U16	10	Read	0.0..100.0%	x	
1400	Power on setpoint Control Area 1 Channel 1	U16	10	Read/Write	0.0..100.0%; 6553.5=last setpoint		x
1401	Power on setpoint Control Area 2 Channel 1	U16	10	Read/Write	0.0..100.0%; 6553.5=last setpoint		x
1402	Power on setpoint Control Area 3 Channel 1	U16	10	Read/Write	0.0..100.0%; 6553.5=last setpoint		x
...							
1499	Power on setpoint Control Area 100 Channel 1	U16	10	Read/Write	0.0..100.0%; 6553.5=last setpoint		x
1500	Power on setpoint Control Area 1 Channel 2	U16	10	Read/Write	0.0..100.0%; 6553.5=last setpoint		x
1501	Power on setpoint Control Area 2 Channel 2	U16	10	Read/Write	0.0..100.0%; 6553.5=last setpoint		x

